

Tabelul 3 Filtrul trece banda cu 3 poli, in configuratie II [$Z_{in} = Z_{out} = 50 \Omega$] :

Banda	Fc min	Fc max	C1 pF	L1 μH	C2 pF	L2 μH	Q min	-dB la Fc / 3	-dB la Fc / 2	-dB la 2*Fc	-dB la 3*Fc
1.8	1.8	2	15915	0.44	88.42	79.58	28	86	71	69	85
3.5	3.5	4	6366	0.28	56.84	31.83	22	76	60	66	80
7	7	7.4	7958	0.06	12.29	39.79	54	102	86	86	101
10	10	10.5	6366	0.04	7.58	31.83	61	104	89	89	104
14	14	14.4	7958	0.02	3.16	39.79	106	118	104	103	118
18	18	18.5	6366	0.01	2.39	31.83	109	119	105	103	118
21	21	21.5	6366	0.01	1.76	31.83	127	123	108	108	123
24	24.5	25	6366	0.01	1.3	31.83	148	127	111	112	127
28	28	30	1592	0.02	3.79	7.96	43	94	79	82	96